



Yur.Beat Dolce

Hi-Fidelity Digital Radio and FM tuner - Digital Audio Broadcasting technology with digital output











create >> excite >> inspire

The Spectrum of Revolution





Yur.Beat Dolce

Digital Audio Broadcasting / FM Radio

Features

- Hi fidelity DAB & FM Radio
- Wooden design for warm audio characteristics
- Stylish LCD with membrane keypads
- High-end audio outputs with Optical S/PDIF, RCA and 3.5mm stereo sockets
- 2 speakers design for full range acoustic spectrums
- 5 DAB Radio presets and 5 FM Radio presets

Specifications

- Compliant with ETS 300 401
- Capable of decoding all DAB transmission modes 1 4 up including 384kbps
- Frequency range:
 - FM: 87 108 MHz
 - Band III: 174 240 MHz
 - L band: 1452 1492 MHz (optional)
- · Speakers: 4" and 2" full range drive units (stereo)
- Input Connectors:
 - 12VDC power
 - RF F-type connector for 75 Ohm DAB aerial (aerial supplied)
 - Output Connectors:
 - 3.5mm headphone
 - Optical (S/PDIF)Toslink connector
 - RCA connector
- Radio Navigation & Controls:
 - Membrane keypad for functions such as:- Volume Up, Volume Down
- Presets 1 5, Scan, Select
- Display: High-visibility 16 x 2 character LCD
- Power Supply: Mains via 230AC to 12V DC external power adapter
- CE and RoHS Compliance
- Warranty: 2 years

Accessories

- Multi-language installation guide and manual
- Power adapter

System requirements:

- Power supply: 100 240V 50/60Hz 0.35A
- DAB broadcast environment and services

Product dimension: 170 x 180 x 170mm (excluding antenna) Weight (kg): 2.5kg

Packaging: 265 x 215 x 218mm Weight (kg): 2.7kg

Carton Box (8 in 1): 550 x 462 x 440mm Weight(kg): 25 kg

Warranty Notice: *2 years Warranty

EAN: 888643700061-

Yuraku Pte Ltd

Ubi Crescent Block 40 #01-02 Ubi Techpark Singapore 408567 Tel: +65 6238 2158 Fax: +65 6238 0076

Website: www.yuraku.com.sg

create >> excite >> inspire